Lebanon Phone Center & Alarm, Inc.

Your Communications & Security Specialists

219 W. Commercial Lebanon, M. 65536 Cel. 417-532-9819 Fax: 417-588-4258

Login into administrator mailbox

From your system phone

Press	voicemail	(voice mail will answer and prompt you to enter your password)
Dial	#	(if you know the extension)
Dial	#	(please enter your mailbox number)
Dial	70	(Please enter you password)
Dial	70	(you have no new messages, main menu)

From you home phone or cell phone

Dial you company phone number and wait for phone system to answer, when greeting starts follow below instructions.

Dial # (please enter your mailbox number)
Dial 70 (Please enter you password)
Dial 70 (very lease enter you password)

Dial 70 (you have no new messages, main menu)

To Record new Day Greeting (box 800)

Login to administrator mailbox

Dial 3 options
Dial 2 greeting
Dial 800 box number

Dial 1 to listen to recorded greeting

Or

Dial 2 to record new greeting

Dial 0-9 for greeting number (you can have up to 10 different greetings)

Or you may dial * for the current active greeting

Follow voice prompts

To Record new Night Greeting (box 801)

Login to administrator mailbox

Dial 3 options
Dial 2 greeting
Dial 801 box number

Dial 1 to listen to recorded greeting

Or

Dial 2 to record new greeting

Dial 0-9 for greeting number (you can have up to 10 different greetings)

Or you may dial * for the current active greeting

Follow voice prompts

To swap greeting 0-9

Login to administrator mailbox

Dial 3 options Dial 2 greeting

Dial 800 or 801 depending if you are changing day greeting or night greeting

Dial 5 to select new greeting

Dial 0-9 for greeting number (you can have up to 10 different greetings)

Follow voice prompts