Lebanon Phone Center & Alarm, Inc.   417-532-9819

SBX CALL FORWARDING

1 > Press [SPEAKER] button.

2 > Press [DND/FWD] button.

Follow-me Forward

0	Follow-me Forward	*Retrieve your station calls From another Station*
		Dial station number to forward, enter security code (voicemail access code) then dial #

Unconditional, Busy, No Answer, Busy/No Answer Forward

1	Unconditional	*Forwards all calls, immediate*
2	Busy	*Only forwards when you are busy on phone*
3	No answer	*Forwards when you don't answer phone*
4	Busy/No answer	*Forwards when your phone is busy or no answer*

Enter forward destination (STA/HUNT/VMIB).

STA: station number, 100-132.

HUNT: Hunt group, 620-629.

VMIB: # (Forward to Voicemail Box)

Unconditional, No Answer Off-net Forward with speed bin *(forward to programmed speed dial #)*
IMPORTANT: *Must have positive disconnect signal from Phone Company on lines*

5	Unconditional
6	No answer

Enter speed bin number.

(Station speed bin :000-099, system speed bin:2000-2499)

Unconditional, No Answer Off-net Forward telephone number *(allows you to enter # forwarding to)*
IMPORTANT: *Must have positive disconnect signal from Phone Company on lines*

8	Unconditional
9	No answer

Enter telephone number. **Press (HOLD/SAVE)**

To Cancel Press (DND/FWD) button